

## RepeaterMBusXL

## Repeater for the M-Bus communication interface

- > M-Bus repeater
- > Versions for connecting 20, 45, 80, 120, 190 M-Bus slave devices.
- > Standard operating voltage range DC 12 to 30V
- > Extended error indication with multiple status LEDs
- > Communication speeds up to 9600bps
- > Protections and filters ensuring high durability of the entire device against surges and failures



### Overview

The M-Bus repeater is used to extend an M-Bus communication line over the standard distance (suitable for cca. over 1km) or galvanic separation of individual M-Bus line sections.

The repeater splits the M-Bus line into two galvanically separated M-Bus lines and enables message transfer between these two lines without message content changes.

Depending on model the M-Bus master port has a connection capacity for 20, 45, 80, 120 or 190 M-Bus slave devices. The interface has the highest rating of surge protection and is resilient to failures on the M-Bus line.

The states of M-Bus master line and the repeater are evaluated and monitored by a processor. Error states are indicated by status LEDs which simplify identification of the repeater's current state and possible causes of a malfunction. The LEDs indicate functionality of the repeater, power source state, M-Bus line loading and possible error states on the line.

The repeater works at a standard level of DC voltages with polarity reversal protection.

### M-Bus slave communication interface

Power consumption	2 slave devices (2UL)
Protection	overvoltage protection TVS 600W
Galvanic separation	>1kV from power supply, 1kV from the M-Bus master line

### M-Bus master communication interface

Number of attachable devices	five versions: 1 to 20, 45, 80, 120, 190 M-Bus slave devices
Baud rate	300 - 9600 bps
Protection	- overvoltage protection TVS 1500W - electronic protection against overloads, short circuit and external voltage on the line. Time of recovery to normal operation within 1 second.
Galvanic separation	1kV from power supply, 1kV from the M-Bus slave line

### Power supply

DC power	12V to 30V. Model XL190 20V to 30V.
Protection	- overvoltage protection TVS 1500W - power source polarity reversal protection
Power consumption	0.85W to 15W Depends on M-Bus line load, power supply, repeater model. Consumption falls to min. value during short and overload on M-Bus line.

### Temperature

Operating range	-40°C to 70°C
-----------------	---------------

## Mechanical parameters

The repeater is made from a robust aluminium box which ensures excellent mechanical durability, enhanced interference resistance and improved heat dissipation from the repeater to the environment. The repeater is designed to be mounted on a 35 mm DIN rail (EN 50022 top hat rail). Weight of the repeaters ranges from 230g to 250g depending on model.



Top view



Side view with DIN rail attached

## LED indication

### **i** Operational states indication

LED	State
<b>Power LED</b> turned on	Repeater and power supply is alright.
<b>Transmit LED</b> flashing	Data is transmitted to the M-Bus line.
<b>Receive LED</b> flashing	Data is received from the M-Bus line.
<b>Meters LED</b> turned on	Load on M-Bus line. Meters are connected to the line.
<b>Meters LED</b> turned off	Disconnected M-Bus line. No meters are connected to the line.
<b>Meters LED</b> fast flashing	Max. amount of meters on M-Bus line reached (2 meters tolerance).

### **!** Malfunction states indication

LED	State
<b>Power LED</b> flashing	Internal repeater error.
<b>Power LED</b> flashing + turned on <b>Err./Coll. LED</b>	External voltage on M-Bus line or Internal repeater error.
<b>Err./Coll. LED</b> flashing or turned on	Repeater overload - too many meters, short on the M-Bus line or capacitive overload on M-Bus line (C of line >5 $\mu$ F). When turning on the power - capacitive overload on M-Bus line (C of line >1 $\mu$ F). Increased capacitance may be caused by meters during power up. Capacitance can afterwards fall below 1 $\mu$ F.
<b>Err./Coll. LED</b> turned on for a short while	During data reception - flashing <b>Receive LED</b> . Communication collision. Simultaneous reply from multiple meters. During data transmission - flashing <b>Transmit LED</b> . An error occurs during transmission (incorrect voltages on the M-Bus line). Internal repeater error or capacitive overload on M-Bus line.

## EMC compatibility

EMC compatibility of the M-Bus repeater has been tested according to the following industrial environment standards in an accredited laboratory.

### EMC emission tests

Standard	Test	Level
EN 55011	Power line - CONDUCTED EMISSIONS 10/150 kHz - 30 MHz	Class A
EN 55011	RADIATED EMISSIONS (Electric Field) 30 MHz - 1000 MHz	Class A

### EMC immunity tests

Standard	Test	Level
EN 61000-4-2	ELECTROSTATIC DISCHARGE (ESD) - Contact discharge	± 4kV
EN 61000-4-2	ELECTROSTATIC DISCHARGE (ESD) - Air discharge	± 8kV
EN 61000-4-3	RADIATED RADIO-FREQUENCY ELECTROMAG. FIELD 80MHz - 1GHz	10 V/m
EN 61000-4-3	RADIATED RADIO-FREQUENCY ELECTROMAG. FIELD 1.4GHz - 2GHz	10 V/m
EN 61000-4-3	RADIATED RADIO-FREQUENCY ELECTROMAG. FIELD 2GHz - 2.7GHz	3 V/m
EN 61000-4-4	ELECTRICAL FAST TRANSIENT/BURST - Power line	± 4 kV
EN 61000-4-4	ELECTRICAL FAST TRANSIENT/BURST - M-Bus line, RS232 line	± 4 kV
EN 61000-4-5	SURGE IMMUNITY - Power line. Common/differential mode.	± 1kV / ± 500 V
EN 61000-4-5	SURGE IMMUNITY - M-Bus line, RS232 line. Cable shielding.	± 4 kV
EN 61000-4-5	SURGE IMMUNITY - M-Bus line. Common/differential mode.*	± 4kV / ± 2kV
EN 61000-4-6	CONDUCTED DISTURBANCES, INDUCED BY RADIO-FREQUENCY FIELDS 0,15MHz - 80 MHz. M-Bus line.	10 V

\* Test carried out at the request of the manufacturer. The M-Bus port of the repeater achieves the highest level of overvoltage protection according to the EN 61000-4-5 standard. Carrying out this type of test is not required with the use of shield cable. Reaching the highest level of protection on the M-Bus port also guarantees the highest achievable reliability of the repeater. The M-Bus interface often poses the greatest risk of overvoltage and the ensuing destruction of the repeater.

## Manufacturer:

JC Elektronika s.r.o.

Address: Bôrická cesta 103, Žilina 010 01 Phone: +421 908 854 675

REG No.: 51 439 255 TAX No.: 2120691606 VAT No.: SK2120691606

WEB: [www.prevodniky.sk](http://www.prevodniky.sk) E-mail: [service@prevodniky.sk](mailto:service@prevodniky.sk), [office@prevodniky.sk](mailto:office@prevodniky.sk)

